CARECALLER

DS1210W WINDOW & DOOR TRANSMITTER



The DS1210W has an internal reed switch on the side and on one end to accommodate any mounting position. Also included is an internal zone input with screw terminals which can be used at simultaneously with the magnet and reed switches.

The gap between the magnet and the switches can be up to 5/8" (16 mm).

The front cover is protected with a tamper switch.

SPECIFICA TIONS

External contact: N/O or N/C

Distance of wire attached

to external contact: 10 feet (3m)

Typical battery life: 4 years

Battery: 3.0V lithium

Panasonic CR123A or equivalent

Operating environment: 32 to 140 degrees F

(0 to 60 degrees C)